

4030M

Passive IFB beltpack with 1/4" (6.3mm) Jack


The RTS model 4030M is a passive single channel listening station. In IFB applications, talent, such as newscasters, musicians, sportscasters, etc. can use the model 4030M to receive director instructions alone or to receive both audio program feed and director instructions. Behind-the-scenes personnel for production coordination and control may also use it. It connects directly to a port of all RTS digital matrix systems.



Features

- Monaural 1/4" phone jack for headphone/earset connection.
- XLR type 3-pin female connector for audio/power connection.
- Volume control is dented to help prevent accidental maladjustment during use.

Line Drawing



Specifications

General

Environmental Requirements

Storage: -20°C to 80°C (-4°F to 176°F); 0% to 95% humidity, non-condensing
Operating: 0°C to 50°C (32°F to 122°F); 0% to 95% humidity, non-condensing
Dimensions: 1.5" (38mm) H, 3.75" (95.3mm) W, 3.65" (92.7mm) D
Weight: 6.2oz (303g)

Interface Requirements

Earset/Headphone Compatibility: Accepts 50 to 600 Ω earsets or headphones

Audio Input Requirements

Input Level: 2Vp-p (0 dBu) nominal
Input Impedance: 2000 Ω \pm 5%

Connector Pin Configurations

Headset Connectors

Type: 1/4" (6.3mm) Monaural Plug
Tip: Headset audio high
Sleeve: Headset audio low

Audio Connector

Type: XLR-3F
Pin 1: Common
Pin 2: Channel 1 audio
Pin 3: Common

Order Information

4030M • 4030M • Passive IFB beltpack with 1/4" (6.3mm) jack

The specification information is preliminary and is subject to change without notification.
Brand names mentioned are the property of their respective companies.