

Quick Start Guide

VLink/VLink LE Virtual Intercom System

System Requirements		NOTE: If you are using multiple NIC (Network Interface Card) cards, be sure you are using the configured card.	
Important:	When you start the VLink Virtual Matrix software for the first time, you must obtain the System Identification of the computer you are running the software. The System Identification number is needed to license the software.	 Hardware Pentium 4, 2.4GHz or better with 4GB memory (requirements may be greater depending on system size) Software Windows Server 2008 (preferred), Windows Server 2003, Windows XP, Windows Vista, or Windows 7 Network 100BaseT connection For more information, see the Network Bandwidth Requirements Guide on page 65 in the System Administration Guide (PN-F01U217816) Firewall Outbound: Allow TCP connection for data on port 1000 and UDP connection for audio on port 1000 Inbound: Port forwarding TCP and UDP on port 1000 to IP Address server 	
Installation Important:	The VLink Virtual Matrix can be run before licensing; however, you cannot connect to the control panel or device interfaces.		



Quick Start Guide





		The System Identicator System Information Image	Taley System Configuration tion Code is a unique value specific to the computer on was installed. This code must be provided to your initial installation to cleme file Matrix to support number of clemts purchased. The ation atio	rs. System Identification Code
Obtain Valid License Code Important: When you receive your		 To obtain a valid license code, do the following: > Using the liscensing contact person information below, send an email to the approprate contact requesting a license code. 		
	license code, save it to your desktop for later use.	Asia (APR Region)	alice.onn@sg.bosch.com	Alice Onn
		Europe, Africa, Middle East (AMEA Region)	NSOOrderDeskExport.STSEC- LOG@de.bosch.com	Susi Betzenhauser Sabina Basic
		Americas (AMEC Region)	buv.orders@us.bosch.com	Lisa Wenger Diane Dressel



Quick Start Guide

Activate VLink	To activate the VLink software application, do the following:		
	Important: System Status fields are color-coded as follows:Red indicates a problem		
	• Yellow indicates a condition needs attention		
	 Green indicates normal operation From the Start menu, select Programs/RTS/VLink System Administration. The System Administration Login window appears. 		
	2. Click Login. The System Administration window appears.		
	WLink System Administration - Default		
	System Information Licensee: Licensed Connections: Dicense Expiration: System Status System Status System Up Time: Od, Oh, 14m Processor Utilization: Processor Utilization: O (0) Failover Status: Not Licensed Active Connections: O of O Active Audio Inputs: O Active Audio Outputs: O Trunking Status System Configuration System Maintenance System Statistics Client Statistics Client Statistics		
	Trunking Status: Not Licensed Active Trunks: 0 of 0 Logout Exit		
	 3. Click the System Information button located in the upper-left corner. <i>The System Identification Code window appears</i>. If Vlink System Idenfication Code - Default Information The System Identification Code is a unique value specific to the computer on which the Virtual Matrix was installed. This code must be provided to your sales representive upon initial installation in order to obtain a License file the enables the Virtual Matrix to support number of clients purchased. The License file is not transferrable to any other computer. 4. Click Upload License File. 		
	 A navigational window appears. 5. Navigate to where you saved the VirtualMatrix.key file. 6. Click Open. The license code is uploaded into the application. 		

Reference: For more detailed information, see the VLink System Administrator's Guide (PN - F01U217816) or the VLink User's Manual (PN - F01U2178150).